## AcuSplitCT Series 1000/1200/1600A Split Core Current Transformer



The Accuenergy split core CTs are compact and low-cost current transformers with high accuracy. The CTs are ideal for quick and easy installation without disconnecting cables during installation. Multiple installation mechanisms provide stable and durable current measurement.

### **FEATURES**

- Most cost-effective
- Safe and easy installations
- Multiple installation mechanisms

# CE CESSOS ROHS COMPLIANT


## **SPECIFICATIONS**


Rated Primary Current	1000A, 1200A, 1600A
Rated Secondary Current	5A, 1A
Burden	7.5VA
	7.0
Accuracy	0.5%
Withstand Voltage	3,000Vac
Frequency range	50-400Hz
Operating Temperature	-15°C - 60°C
Standard	IEC 60044-1
Case Material	UL flame retardant rating 94-V0
Certifications	UR, CE approved & RoHS compliant


ORDERIN	IG INFO	RMATI <i>(</i>	NC

ORDERING IN ORIGINATION				
	Rated Input			
Ordering Number: AcuCT- 3147	-	-		
Ordering Example: AcuCT- 3147	- 1600	- 5		
	1000: 1000A	5: 5A		
	1200: 1200A	1:1A		
	1600· 1600A			

## **DIMENSIONS**











Tel.: 2280-1686 • Fax: 2524-2397 ventas@eproteca.com • www.eproteca.com